


PDV in a Railgun

*The Institute for Advanced Technology
The University of Texas at Austin*

Scott Levinson, Sikhanda Satapathy, Dwight Landen,

**2nd Annual PDV Workshop
Aug 16-17, 2007
Lawrence Livermore National Laboratory**


Electromagnetic Launcher



The current flowing in the rails causes a magnetic field which interacts with the current in the armature, generating a Lorentz ($J \times B$) force.

Energy Balance:

$$\int_0^t VI dt = \int dE_m + \int_0^t RI^2 dt + \int F_z dz$$



Faraday's Law:

$$V = RI + \frac{\partial \phi}{\partial t}$$

$$\Rightarrow E_m = \int Id\phi - \int F_z dz$$

$$\Rightarrow F_z = - \left. \frac{\partial E_m}{\partial z} \right|_{\phi} ; \text{ and } I = \left. \frac{\partial E_m}{\partial \phi} \right|_z$$

$$\Rightarrow F_z = - \frac{\partial}{\partial z} \left(\frac{\phi^2}{2L} \right) = \frac{1}{2} \frac{\partial L}{\partial z} I^2$$



This is a geometric parameter.

Railgun Equations

- Propulsion force:

$$F = ma = \frac{1}{2} L' I^2 - F_f$$

- L' is the “inductance gradient”, a geometric constant, and is around $0.5 \mu\text{H/m}$

$$F_f = \frac{1}{2} L' I^2 - m\dot{v}$$

Measured with Pearson coil


Measured with PDV method

Why is Friction Measurement Important?




- The start-up region requires initial external contact pressure to carry current.
- Due to long residence time of the armature at the start-up region, abnormal damage occurs to both rail and armature.
- Role of lubrication in the interface is under study.
- Accurate measurement of the initial motion is extremely important for studying lubrication effects.


Typical measurement from B-Dot probes



Breech Current Shot 6



Axial Velocity Measurements with PDV on 1 m Railgun at IAT



← 1 m →



3M
μRetroReflective
Surfaces

Beech Probe




Muzzle Probe

2 independent axial
velocity
measurements
With PDV



$$v_i = 0.775 \frac{\text{m/s}}{\text{MHz}} \Delta f_i$$

Breach Probe & Leading & Trailing Edges of Launch Package




Breech & Muzzle Probe Spectrograms 1 m Railgun


$$|s(\Delta f, t)|^2 = S(\Delta f, t) \rightarrow S(v, t) \quad v = 0.775 \frac{\text{m/s}}{\text{MHz}} \Delta f_i$$

Muzzle Probe

Breech Probe (bracketed)



t (ms)




t (ms)

$$S(t) = \max_k |s(\Delta f_k, t)|^2 = \max_k |s(v_k, t)|^2$$


$$S(t)/N(t) \cong \frac{S(t)}{\sum_{k=1}^{2048} |s(v_k, t)|^2 - S(t)}$$

Muzzle Probe

Breech Probe






t (ms)




t (ms)


Muzzle Probe ↓

Breech Probe ↓










Breech (C2) & Muzzle Velocities (C4) PDVanalMeIShot6 N:4096 novlap: 2048



Acceleration Statistics C3PDVanaIMELshot6: 7-order, scaled & centered Poly Fits



t - ms




- Accurate velocity measurement is possible by measuring Doppler shift.
- Motion measurement is possible in the start-up region where use of B-dot probes is problematic.
- This method will help assess effects of lubrication on start-up armature behavior.
- The data shows interesting dynamic friction behavior at sliding contact.
- Future work: direct measurement of acceleration

[1] "High resolution sliding velocity measurement for assessing dynamic friction effects," Sikhanda Satapathy, Scott Levinson, Dwight Landen, David Holtkamp, and Adam Iverson, ASME Applied Mechanics and Materials Conference
June 3-7, 2007, University of Texas at Austin


Next Let's Consider:

- Direct measurement of acceleration Incorporating VISAR principals
- Quick Look at Long range (18 m) and poor reflecting surfaces
- Feasibility of using Multiple probes for balloting measurement



Detected signal: $s(t) \cong 2 \cdot \sqrt{\bar{I}_{0\bar{t}} \cdot \bar{I}_{1\bar{t}}} \cos(\Delta\omega(t) \cdot t) = 3.8 \text{ V/mW} \cdot \sqrt{\bar{I}_{0\bar{t}} \cdot \bar{I}_{1\bar{t}}} \cos\left\{2\omega_0 \frac{v_{\bar{t}} + a_{\bar{t}} \cdot t}{c} t\right\}$.

Terms incorporated in a subscript \bar{t} indicate that they are calculated or measured by averaging over a small time interval τ centered about \bar{t} . Note that the amplitude of the detected signal $|s(t)|$ is proportional to the square-root of the received signal amplitude ($\sqrt{\bar{I}_{1\bar{t}}}$), and is adjustable by simply varying laser source amplitude ($\sqrt{\bar{I}_{0\bar{t}}}$).



$$S(t) \cong 3.8V/mW \left(\begin{aligned} &\sqrt{I_{0\bar{t}} \cdot I_{1a\bar{t}}} \cos((\omega_0 - \omega_{1a}) \cdot t) + \sqrt{I_{0\bar{t}} \cdot I_{1b\bar{t}}} \cos((\omega_0 - \omega_{1b}) \cdot t) \\ &+ \sqrt{I_{1a\bar{t}} \cdot I_{1b\bar{t}}} \cos((\omega_{1a} - \omega_{1b}) \cdot t) \end{aligned} \right)$$

Noting: $\omega_1(t) = \omega_0 \left(1 + \frac{2v(t)}{c} \right)$, we observe that

$$\omega_{1a} = \omega_0 \left(1 + 2 \frac{\bar{v}_{\bar{t}} + \bar{a}_{\bar{t}} \cdot (T_a - \bar{t})}{c} \right)$$

$$\omega_{1b} = \omega_0 \left(1 + 2 \frac{\bar{v}_{\bar{t}} + \bar{a}_{\bar{t}} \cdot (T_b - \bar{t})}{c} \right)$$

"VISAR-Like" PDV for Acceleration cont.

Three signal components offer an independent means to detect the velocity in the vicinity of time T_a and T_b , and with average acceleration between them. They have respective frequencies & amplitudes:

$$1) \quad |\omega_{1a} - \omega_0| = 2\omega_0 \frac{\bar{v}_{\bar{t}} + \bar{a}_{\bar{t}} \cdot (T_a - \bar{t})}{c} \quad \text{at amplitude } \sqrt{I_{0\bar{t}} \cdot I_{1a\bar{t}}}$$


$$2) \quad |\omega_{1b} - \omega_0| = 2\omega_0 \frac{\bar{v}_{\bar{t}} + \bar{a}_{\bar{t}} \cdot (T_b - \bar{t})}{c} \quad \text{at amplitude } \sqrt{I_{0\bar{t}} \cdot I_{1b\bar{t}}}$$

$$3) \quad |\omega_{1b} - \omega_{1a}| = 2\omega_0 \frac{\bar{a}_{\bar{t}} \cdot (T_b - T_a)}{c} \quad \text{at amplitude } \sqrt{I_{1a\bar{t}} \cdot I_{1b\bar{t}}}$$

The 3rd component's frequency is **proportional to acceleration** \Rightarrow **directly measurable!**

However, it's amplitude, $\sqrt{I_{1a\bar{t}} \cdot I_{1b\bar{t}}}$, is typically 10-20 dB smaller than the other 2 components \Rightarrow **may result in poor S/N.**


150 mW - each channel



75 mW - each channel



300 mW - each channel




← 0.85 in →




Trial 5: Moving RetroReflective Surface

300 mW - each channel, Adjustable Retro: - 2 dB each ch

Probe - Reflector Range: 18.0 m







$S(v,t)$



t - ms

t - ms

$$S(v,t)$$



t - ms





Trial 4: Moving RetroReflective Surface

75 mW - each channel, Adjustable Retro: - 6dB each ch

Probe - Reflector Range: 18.0 m




$S(v,t)$



t - ms

t - ms


Use Multiple (Muzzle) Probes



Muzzle Probe Array (Oz Optics)



Muzzle Mirror




Downrange into Muzzle Mirror (1-mW 650 nm signal from FIS "Fault Detector" split into 3 probes)

Up-range into IR card at breech (IR Laser signal from each probe)₂₆

Breech and Muzzle Velocities with new Laser (with appropriate bracketing)



pdv001_Ch4.wfm taken: 25-Jun-2007 13:44:54 N:16384 novlap: 8192



- Like VISAR, use of time delayed signals may allow direct PDV measurement of the acceleration
- A Quick-look shows PDV is likely to work over
 - long ranges,
 - with multiple, independent, closely-spaced signals,
 - & (maybe) w/ untreated launch-package surfaces.
- Multiple-independent signal detection in small railgun is feasible
- Future work:
 - Routinely characterize axial velocity profiles in large EM guns (e.g., HeMCL)
 - Test direct measurements of axial acceleration & 3d balloting

[1] "Photonic Doppler Velocimetry in the Bore of a Railgun", <http://www.emlsymposium.org/about.html>,

[2] "High resolution acceleration measurements," <http://www.emlsymposium.org/about.html>


[3] "Balloting Motion Measurement in Railgun," <http://www.emlsymposium.org/about.html>



Extras






Spectrogram of New Laser




Multiple Velocities result from aliasing & multiple lines (1.667 GHz)
 (from new IPG Laser, which is now fixed)

Trial 8: No Moving Surface

300 mW - each channel, Adjustable Retro: - 2 dB each ch
 Probe - Reflector Range: 18.0 m




V - m/s





t - ms

t - ms




S

S/N



Tektronix
Scope ⇒
Traces




t - ms

t - ms

Trial 5: Moving RetroReflective Surface



300 mW - each channel, Adjustable Retro: - 2 dB each ch

Probe - Reflector Range: 18.0 m




S

S/N





Tektronix
Scope \Rightarrow
Traces




t - ms

t - ms




S

S/N




Tektronix
Scope ⇒
Traces





t - ms

t - ms




S

S/N



Tektronix
Scope \Rightarrow
Traces



t (ms)

t (ms)