

Optical Receiver Module Evaluation for PDV

Michael Rutkowski
Araceli Rutkowski
NSTec, Los Alamos Operations
August 16, 2007

Design Goals

- Design an optical PDV receiver by integrating optical components (optical splitters, circulator, attenuator, etc) with the MITEQ optical detector in a single modular package.
- PDV module must be easy to use and adjust.
- Design the PDV receiver module so that it can be fabricated using contract manufacturing.

Acknowledgements

NSTec

David Esquibel

Eduardo Rodriguez

Howard Dexter

Doug Devore

Vince Romero

Claudio Lopez


Adam Iverson

LANL


Dave Holtkamp

8-Channels of PDVs 3U Rack Mount





PDV Receiver swept-wavelength Frequency Response using Agilent's tunable and IPG lasers





- Not all MITEQ detectors have a 3dB cutoff at 14GHz.
- MITEQ detectors have a specified 3dB cutoff at 13GHz.
- Each MITEQ detector has a different optical to electrical conversion gain.

PDV Receiver Output Level

Linear scale


Log scale




- The output level is lowest at 14GHz because of the 3dB frequency cutoff.
- The output level can be calculated from the unshifted (laser input) and shifted (probe) optical powers at the MITEQ detector and its optical to electrical conversion gain.
- Digitizer input range can be set from the calculation.

PDV Receiver Frequency Response for different probe optical powers

Linear scale




Log scale




- As expected, the frequency response remains approximately the same for different probe optical powers.
- 1dB change in the optical power at the probe input will cause about 1dB change at the output.

Optical Receiver Signal to Noise ratio in 12GHz Bandwidth

Linear scale




Log scale




- Signal to noise ratio is affected by the receiving system bandwidth; the higher the bandwidth the lower the signal to noise ratio.
- A negative SNR just means that the signal will be indistinguishable from the system noise.
- Unshifted (laser input) light at the optical receiver is at 0dBm
- Dynamic range: 40 – 50 dB

PDV Receiver Optical Power Meters Error




- Eigenlight's in line power meters have been used in most of the PDV systems.
- Eigenlight meter has been used as a baseline for the PDV receiver power meters evaluation.
- Eigenlight meters have an absolute accuracy specification of $\pm 0.2\text{dB}$.

Optical Assembly Diagram



Optical fibers are trimmed and welded as indicated on the above drawing.

PDV Optical Receiver Module Top View



PDV Optical Receiver Module Front View



Projected Cost for Budgetary Purposes

- Power Supply and Rack \$5K
- PDV Module \$9K
- Rack with 8 PDV Modules \$77K
- Rack with 4 PDV Modules \$41K
- First delivery – 6 months
 - No contract manufacturer has been identified
 - Contract will have to go through the “purchasing” process

Conclusions

- Modules can be easily replaced.
- System can be totally fabricated using contract manufacturing.
- Facilitates the implementation of a PDV system.
- There's a performance record associated with each module.
- Performance over temperature is work in progress.
- Dave Holtkamp has used this system to collect Hydro data.

Contact Information

John Hollabaugh, hollabjs@nv.doe.gov (505) 663-2000

Araceli Rutkowski, diazga@nv.doe.gov (505) 663-2052

Dave Holtkamp, dholtkamp@lanl.gov (505) 667-8082

QUESTIONS